

[B] Board Parts Modification List

****Only mount these parts if a 1080i source cannot be seen after changing "HDPT"**

Reference Number	Value	Part Number
R3035	100 ohm chip	1-216-809-91
R3036	100 ohm chip	1-216-809-91
R3037	100 ohm chip	1-216-809-91
R3038	560 ohm chip	1-218-686-91
R3039	560 ohm chip	1-218-686-91
R3040	560 ohm chip	1-218-686-91
R3984	10 ohm RN:CP	1-218-644-91
R3985	10 ohm RN:CP	1-218-644-91
R3986	10 ohm RN:CP	1-218-644-91
Q3005	2SD601A	8-729-422-26
Q3006	2SD601A	8-729-422-26
Q3007	2SD601A	8-729-422-26
C3442	10uF Electrolytic SMT	1-126-394-21
C3474	10uF Electrolytic	1-124-779-21
C3490	10uF Electrolytic	1-124-779-21
C3402	10uF Electrolytic	1-124-779-21
C3491	47uF Electrolytic SMT	1-126-396-21
C3492	0.1uF F:chip	1-164-156-91
C3493	47uF Electrolytic SMT	1-126-396-21
R3826	100 ohm chip	1-216-809-91
R3435	100 ohm chip	1-216-809-91
R3436	100 ohm chip	1-216-809-91
R3437	100 ohm chip	1-216-809-91
R3438	100 ohm chip	1-216-809-91
R3439	100 ohm chip	1-216-809-91
R3440	100 ohm chip	1-216-809-91
R3441	100 ohm chip	1-216-809-91
L3418	10uH	1-469-555-21
C3500	100uF Electrolytic SMT	1-126-392-21
C3501	0.1uF F:chip	1-164-156-91
IC3413	TC74LVX157FT	6-700-205-01
IC3414	M52055FP	8-759-548-56
R3801	#	remove mounted part
R3818	#	remove mounted part
R3819	#	remove mounted part
R3453	#	remove mounted part
R3456	#	remove mounted part
R3881	68 ohm chip	1-216-807-91
R3882	68 ohm chip	1-216-807-91
R3883	68 ohm chip	1-216-807-91