



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER: 150-4H
 Cone Kit: C8RE145
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 10
 Sweep Frequency Hz: 20-1200
 D.C. Resistance Ohms: 5.2 min/6.4 max
 Gap Gauge: .057"
 Notes:
 If Not Serviceable, Replace With: Currently Available.
 Can Also be replaced with E145-8
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes

MID RANGE DRIVER: 2425H
 Cone Kit: D8R2425
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 2.85
 Sweep Frequency Hz: 550-1200
 D.C. Resistance Ohms: 2.9 min/3.5 max
 Gap Gauge: .031"
 Notes:
 If Not Serviceable, Replace With: 2426H
 Visual Change: No

MID RANGE DRIVER (Cont'd)
 Baffle Modification: No
 Exact Acoustic Replacement: Yes

HIGH FREQUENCY DRIVER: 2405H
 Diaphragm Kit: D16R2405
 Nom. Impedance: 16 Ohm
 Dynamic Test Input V: 7
 Sweep Frequency Hz: 1000-3000
 D.C. Resistance Ohms: 5.7 min/6.7 max
 Gap Gauge: .025"
 Notes:
 If Not Serviceable, Replace With: Test With Network
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A

SYSTEM SPECIFICATIONS:
 Nom. Impedance: 8 ohm
 Rec. Amp Power: 250 Watts Per Channel
 Crossover Frequencies: 850 Hz, 7500 Hz
 Sensitivity: 100dB (1 Watt @ 1 Meter)
 Enclosure Dim: 55-1/8" x 36" x 20" D
 141cm x 92cm x 51cm
 Weight: 320 lbs. - 145 kg.

*Other parts may also be available. Check with JBL for details.