



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER: 306G-3
 Cone Kit: Kit not available.
 Defective driver should be replaced.
 Nom. Impedance: 4 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 30-1200
 D.C. Resistance Ohms: 4.6 min/5.8 max
 Gap Gauge: N/A
 Notes:
 If Not Serviceable, Replace With: Currently Available
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A

HIGH FREQUENCY DRIVER: 012
 Diaphragm Kit: Kit not available.
 Defective driver should be replaced.
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 1000-2000

HIGH FREQUENCY DRIVER (Cont'd)

D.C. Resistance Ohms: 3.6 min/4.4 max
 Gap Gauge: N/A
 Notes: Test With Network
 If Not Serviceable, Replace With: Currently Available
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A

SYSTEM SPECIFICATIONS:

Nom. Impedance: 8 Ohm
 Rec. Amp Power Range: 10-75 Watts Per Channel
 Crossover Frequency: 3600 Hz
 Sensitivity: 89dB (1 Watt @ 1 Meter)
 Enclosure Dim: 14-3/4" x 10" x 9-1/4" D
 375mm x 254mm x 235mm
 Shipping Weight: 39 lbs./pair - 17.7 kg./pair
 Additional Parts Currently Available*:
 Grill: GJ216A
 Binding Posts: Red: 63635
 Black: 63636

*Other parts may also be available. Check with JBL for details.