



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

- 308G-2
- Cone Kit: C4R308G-2
- Nom. Impedance: 4 Ohm
- Dynamic Test Input V: 5
- Sweep Frequency Hz: 30-1200
- D.C. Resistance Ohms: 4.8 min/5.9 max
- Gap Gauge: .051"
- Notes:
- If Not Serviceable, Replace With: 308G-1 or 508G
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No. Slightly different.
- Replace both units in a stereo pair.

Additional Parts Currently Available*:

- Dome: 61521
- Mounting Gasket: 59707

MID RANGE DRIVER:

- 305G-2
- Cone Kit: C4R305G-2
- Nom. Impedance: 4 Ohm
- Dynamic Test Input V: 4
- Sweep Frequency Hz: 75-3000
- D.C. Resistance Ohms: 3.8 min/4.6 max
- Gap Gauge: .040"
- Notes:
- If Not Serviceable, Replace With: Currently Available
- Visual Change: N/A
- Baffle Modification: N/A
- Exact Acoustic Replacement: N/A

MID RANGE DRIVER (Cont'd)

Additional Parts Currently Available*:

- Dome: 54721

HIGH FREQUENCY DRIVER:

- 011
- Diaphragm Kit: Diaphragm Kit not available. Defective driver should be replaced.
- Nom. Impedance: 4 Ohm
- Dynamic Test Input V: 3
- Sweep Frequency Hz: 2000-12000
- D.C. Resistance Ohms: 2.7 min/3.3 max
- Gap Gauge: N/A
- Notes:
- If Not Serviceable, Replace With: 012
- Visual Change: Yes
- Baffle Modification: Yes
- Exact Acoustic Replacement: No. Slightly different.
- Replace both units in a stereo pair.

SYSTEM SPECIFICATIONS:

- Nom. Impedance: 8 Ohm
- Rec. Amp Power Range: 10-100 Watts Per Channel
- Crossover Frequencies: 1000 Hz, 6000 Hz
- Sensitivity: 89dB (1 Watt @ 1 Meter)
- Enclosure Dim: 23" x 12-3/4" x 9-1/4" D
584mm x 324mm x 235mm
- Shipping Weight: 36 lbs. - 16.4 kg.
- Additional Parts Currently Available*:
- Grill: G320
- Binding Posts: Red: 63635
Black: 63636

*Other parts may also be available. Check with JBL for details.