



### SYSTEM COMPONENTS:

<b>LOW FREQUENCY DRIVER:</b>	LE14A
Cone Kit:	C8RLE14A
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	8
Sweep Frequency Hz:	30-1200
D.C. Resistance Ohms:	5.9 min/7.1 max
Gap Gauge:	.057"
Notes:	Aquaplas On Front And Back Of Cone
If Not Serviceable, Replace With:	LE14H-1
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Slightly different.
	Replace both units in a stereo pair.
<b>Additional Parts Currently Available*:</b>	
Dome:	50201
Mounting Gasket:	20253
Trim Gasket:	21811

<b>HIGH FREQUENCY DRIVER:</b>	LE175
Diaphragm Kit:	D16R2410
Nom. Impedance:	16 Ohm
Dynamic Test Input V:	3.5

### HIGH FREQUENCY DRIVER (Cont'd)

Sweep Frequency Hz:	550-1200
D.C. Resistance Ohms:	5.9 min/7.0 max
Gap Gauge:	.031"
Notes:	1217 Horn & 1290 Lens No Longer Available
If Not Serviceable, Replace With:	2425J
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Slightly different.
	Replace both units in a stereo pair.

### SYSTEM SPECIFICATIONS:

Nom. Impedance:	8 Ohm
Power Capacity:	50 Watts Continuous Program
Crossover Frequency:	1500 Hz
Sensitivity:	78dB (1 Watt @ 15 Feet)
Enclosure Dim:	23" x 17-1/2" x 12-1/2" D 58cm x 44cm x 32cm
Shipping Weight:	86 lbs. - 39 kg.
<b>Additional Parts Currently Available*:</b>	
Binding Posts:	Red: 10243 Black: 10244

\*Other parts may also be available. Check with JBL for details.