



SYSTEM COMPONENTS:

- LOW FREQUENCY DRIVER:**
- LE111A
 - Cone Kit: C8RLE111A
 - Nom. Impedance: 8 Ohm
 - Dynamic Test Input V: 6
 - Sweep Frequency Hz: 20-1200
 - D.C. Resistance Ohms: 5.5 min/6.5 max
 - Gap Gauge: .053"
 - Notes: Aquaplas On Back Of Cone
 - If Not Serviceable, Replace With: LE10H-1
 - Visual Change: Yes
 - Baffle Modification: No
 - Exact Acoustic Replacement: No. Use as last resort.
 - Replace both units in a stereo pair.
 - Additional Parts Currently Available*:
 - Dome: 31385
 - Mounting Gasket: 21770
 - Trim Gasket: 21813
- MID RANGE DRIVER:**
- LE5-10
 - Cone Kit: C8RLE510
 - Nom. Impedance: 8 Ohm
 - Dynamic Test Input V: 4
 - Sweep Frequency Hz: 75-3000
 - D.C. Resistance Ohms: 4.9 min/6.1 max
 - Gap Gauge: .040"
 - Notes: Currently Available
 - If Not Serviceable, Replace With: Currently Available or LE5-12
 - Visual Change: Yes
 - Baffle Modification: No
 - Exact Acoustic Replacement: Yes

- MID RANGE DRIVER (Cont'd)**
- Additional Parts Currently Available*:
- Dome: 51686
 - Mounting Gasket: 21771
 - Trim Gasket: 29931
- HIGH FREQUENCY DRIVER:**
- 033
 - Diaphragm Kit: D8R033
 - Nom. Impedance: 8 Ohm
 - Dynamic Test Input V: 5
 - Sweep Frequency Hz: 200-1200
 - D.C. Resistance Ohms: 3.6 min/4.4 max
 - Gap Gauge: .031"
 - Notes: Test With Network
 - If Not Serviceable, Replace With: No replacement available.
 - 034 not safe for L110 System.
 - Visual Change: N/A
 - Baffle Modification: N/A
 - Exact Acoustic Replacement: N/A
 - Additional Parts Currently Available*:
 - Mounting Gasket: 57754

SYSTEM SPECIFICATIONS:

- Nom. Impedance: 8 Ohm
- Power Capacity: 75 Watts Continuous Program
- Crossover Frequencies: 1000 Hz, 4000 Hz
- Sensitivity: 89dB (1 Watt @ 1 Meter)
- Enclosure Dim: 23-1/2" x 14-1/4" x 11-1/4" D
- 597mm x 362mm x 286mm
- Shipping Weight: 50 lbs. - 23 kg.
- Additional Parts Currently Available*:
 - Binding Posts: Red: 56131
 - Black: 56130

*Other parts may also be available. Check with JBL for details.