



**SYSTEM COMPONENTS:**

**LOW FREQUENCY DRIVER:**

- 136A
- Cone Kit: C8R2235
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 10
- Sweep Frequency Hz: 20-1200
- D.C. Resistance Ohms: 5.8 min/6.8 max
- Gap Gauge: .057"
- Notes: Mass Ring
- If Not Serviceable, Replace With: 2235H
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No. Slightly different.  
Replace both units in a stereo pair.

**Additional Parts Currently Available\*:**

- Dome: 50201
- Mounting Gasket: 34499
- Trim Gasket: 52347

**HIGH FREQUENCY DRIVER:**

- LE85
- Diaphragm Kit: D16R2421
- Nom. Impedance: 16 Ohm
- Dynamic Test Input V: 3.5

**HIGH FREQUENCY DRIVER (Cont'd)**

- Sweep Frequency Hz: 550-1200
- D.C. Resistance Ohms: 5.9 min/7.0 max
- Gap Gauge: .031"
- Notes:
- If Not Serviceable, Replace With: 2425J
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No. Slightly different.  
Replace both units in a stereo pair.
- Additional Parts Currently Available\*:
- Horn: H91 (Lens L91 No Longer Available)

**SYSTEM SPECIFICATIONS:**

- Nom. Impedance: 8 Ohm
- Power Capacity: 150 Watts Continuous Program
- Crossover Frequency: 800 Hz
- Sensitivity: 80dB (1 Watt @ 15 Feet)
- Enclosure Dim: 32-3/4" x 23-7/8" x 21-1/4" D  
83cm x 61cm x 54cm
- Shipping Weight: 131 lbs. - 59.4 kg.
- Additional Parts Currently Available\*:
- Binding Posts: Red: 10243  
Black: 10244

\*Other parts may also be available. Check with JBL for details.