



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

125A
 Cone Kit: C8R127A
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 5
 Sweep Frequency Hz: 30-1200
 D.C. Resistance Ohms: 4.7 minimum
 5.7 maximum

Gap Gauge: .044"
 Notes: Dome Inverted

If Not Serviceable,
 Replace With: 125HR
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No.
 Slightly different. Replace both units
 in a stereo pair.

Additional Parts Currently Available*:

Dome: 50201
 Terminal Board: 52348
 Mounting Gasket: 52089
 Trim Gasket: 52315

MID RANGE DRIVER:

LE5-6
 Cone Kit: C8RLE510
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 75-3000
 D.C. Resistance Ohms: 5.6 minimum
 6.8 maximum

Gap Gauge: .040"
 Notes:
 If Not Serviceable,
 Replace With: Currently Available.
 Can Also Be Replaced With LE5-12.
 Visual Change: Yes
 Baffle Modification: No

MID RANGE DRIVER (Cont'd)

Exact Acoustic Replacement: Yes

HIGH FREQUENCY DRIVER:

LE25-4
 Diaphragm Kit: D8RLE254
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 3
 Sweep Frequency Hz: 500-1200
 D.C. Resistance Ohms: 3.7 minimum
 4.2 maximum

Gap Gauge: .029"
 Notes: Kit includes parts
 for similar models. Use required parts only.

If Not Serviceable,
 Replace With: 035TiA
 Visual Change: Yes
 Baffle Modification: Yes
 Exact Acoustic Replacement: No.

Slightly different. Replace both units
 in a stereo pair.

Additional Parts Currently Available*:

Trim Ring: 54279
 Mounting Gasket: 50949-01
 Dome: 21606

SYSTEM SPECIFICATIONS:

Nominal Impedance: 8 Ohm
 Power Capacity: 50 Watts
 Crossover Frequencies: Continuous Program
 1500 Hz, 6000 Hz
 Sensitivity: 76dB (1 Watt @ 15 Feet)
 Enclosure Dim: 13-1/2" x 24" x 13-5/8" D
 343mm x 610mm x 346mm
 Shipping Weight: 45 lbs. - 20.4 kg.
 Additional Parts Currently Available*:
 Binding Posts: Red: 56131
 Black: 56130

*Other parts may also be available. Check with JBL for details.