

Technical Manual

L80 Caprice



N/A

SYSTEM COMPONENTS:

FULL RANGE DRIVER:	LE8T
Cone Kit:	C8RLE8T
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	4
Sweep Frequency Hz:	20-1200
D.C. Resistance Ohms:	5.1 minimum 5.9 maximum
Gap Gauge:	.048"
Notes:	Aquaplas On Cone.
Bond 2 foam pads to underside of dome.	
If Not Serviceable,	
Replace With:	LE8T-H
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No.
Slightly different. Replace both units in a stereo pair.	
Additional Parts Currently Available*:	
Dome:	21219
Mounting Gasket:	21769
Trim Gasket:	21812

PASSIVE RADIATOR:	PR8
Cone Kit:	CRPR8

PASSIVE RADIATOR (Cont'd)

Notes:	
If Not Serviceable,	No Replacement Available
Replace With:	N/A
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	
Dome:	21219
Mounting Gasket:	21769
Trim Gasket:	21812

SYSTEM SPECIFICATIONS:

Nominal Impedance:	8 Ohm
Power Capacity:	35 Watts Continuous Program
Crossover Frequency:	N/A
Enclosure Dim:	17-9/16" (including legs) x 22-1/16" x 10" D 446mm x 560mm x 254mm
Shipping Weight:	68 lbs. - 30.8 kg. (Pair)
Additional Parts Currently Available*:	

*Other parts may also be available. Check with JBL for details.