



**SYSTEM COMPONENTS:**

**LOW FREQUENCY DRIVER:**  
 117H-1  
 Cone Kit: C8R117  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 5  
 Sweep Frequency Hz: 30-1200  
 D.C. Resistance Ohms: 5.0 minimum  
 6.0 maximum

Gap Gauge: .051"  
 Notes: Aquaplas On Cone  
 If Not Serviceable,  
 Replace With: 116H-3  
 Visual Change: Yes  
 Baffle Modification: No  
 Exact Acoustic Replacement: No. Slightly  
 different. Replace both units in a stereo pair.

Additional Parts Currently Available\*:  
 Dome: 62112  
 Mounting Gasket: 52671  
 Trim Gasket: 52316

**MID RANGE DRIVER:**  
 LE5-12  
 Cone Kit: C8RLE510  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 4  
 Sweep Frequency Hz: 75-3000  
 D.C. Resistance Ohms: 4.9 minimum  
 6.1 maximum

Gap Gauge: .040"  
 Notes:  
 If Not Serviceable,  
 Replace With: Currently Available  
 Visual Change: N/A  
 Baffle Modification: N/A  
 Exact Acoustic Replacement: N/A

Additional Parts Currently Available\*:

**MID RANGE DRIVER (Cont'd)**

Dome: 51686  
 Mounting Gasket: 21771  
 Trim Gasket: 29931  
 Terminal Board: 53225

**HIGH FREQUENCY DRIVER:**

034  
 Diaphragm Kit: D8R034  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 2.5  
 Sweep Frequency Hz: 200-2000  
 D.C. Resistance Ohms: 5.4 minimum  
 6.6 maximum

Gap Gauge: .031"  
 Notes: Test With Network

If Not Serviceable,  
 Replace With: Currently Available  
 Visual Change: N/A  
 Baffle Modification: N/A  
 Exact Acoustic Replacement: N/A  
 Additional Parts Currently Available\*:  
 Mounting Gasket: 57754  
 Screen: 60424  
 Screen Gasket: 60752

**SYSTEM SPECIFICATIONS:**

Nominal Impedance: 8 Ohm  
 Max Recommended  
 Amp Power: 200 Watts Per Channel  
 Crossover Frequencies: 800 Hz, 3700 Hz  
 Sensitivity: 88dB (1 Watt @ 1 Meter)  
 Enclosure Dim: 21-3/8" x 13" x 10" D  
 543mm x 330mm x 254mm  
 Shipping Weight: 35 lbs. - 16 kg.  
 Additional Parts Currently Available\*:  
 Binding Posts: Red: 56131  
 Black: 56130

\*Other parts may also be available. Check with JBL for details.