



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

- LE10A
- Cone Kit: C8RLE10A
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 6
- Sweep Frequency Hz: 20-1200
- D.C. Resistance Ohms: 4.4 min/5.0 max
- Gap Gauge: .048"
- Notes: Aquaplas On Cone. Dome Inverted.

- If Not Serviceable, Replace With: LE10H-1
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No. Slightly different.
- Replace both units in a stereo pair.

- Additional Parts Currently Available*:
- Dome: 21514
 - Mounting Gasket: 21770
 - Trim Gasket: 21813

MID RANGE DRIVER:

- LE5-3
- Cone Kit: C8RLE59
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 4
- Sweep Frequency Hz: 75-3000
- D.C. Resistance Ohms: 5.6 min/6.6 max
- Gap Gauge: .040"
- Notes: Dome Inverted
- If Not Serviceable, Replace With: LE5-10
- Visual Change: Yes

MID RANGE DRIVER (Cont'd)

- Baffle Modification: No
- Exact Acoustic Replacement: No. Slightly different.
- Replace both units in a stereo pair.

HIGH FREQUENCY DRIVER:

- LE20-1
- Diaphragm Kit: D8RLE20
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 6
- Sweep Frequency Hz: 1000-6000
- D.C. Resistance Ohms: 3.7 min/4.2 max
- Gap Gauge: .029"
- Notes: Test With Network
- If Not Serviceable, Replace With: 035TiA
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No. Use as last resort. Replace both units in a stereo pair.

- Additional Parts Currently Available*:
- Trim Ring: 21600

SYSTEM SPECIFICATIONS:

- Nom. Impedance: 8 ohm
- Power Capacity: 50 Watts Continuous Program
- Crossover Frequencies: 500 Hz, 4000 Hz
- Sensitivity: 70dB (1 Watt @ 15 Feet)
- Enclosure Dim: 20" x 20" x 13" D
- Shipping Weight: 55 lbs. - 25 kg.

*Other parts may also be available. Check with JBL for details.