



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:	123A-2
Cone Kit:	C8R2212
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	6
Sweep Frequency Hz:	20-1200
D.C. Resistance Ohms:	4.5 min/5.5 max
Gap Gauge:	.048"
Notes:	Aquaplas Dome Inverted.
If Not Serviceable, Replace With:	2213H (Reverse Polarity)
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Slightly different. Replace both units in a stereo pair.
Additional Parts Currently Available*:	
Dome:	21514
MID RANGE DRIVER:	LE5-2 (2)
Cone Kit:	C8RLE52
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	4
Sweep Frequency Hz:	75-3000
D.C. Resistance Ohms:	5.5 min/6.5 max
Gap Gauge:	.040"
Notes:	Dome Inverted
If Not Serviceable, Replace With:	LE5-10
Visual Change:	Yes
Baffle Modification:	No

MID RANGE DRIVER (Cont'd)	
Exact Acoustic Replacement:	No. Slightly different. Replace both units in a stereo pair.
Additional Parts Currently Available*:	
Dome:	54721
Trim Gasket:	29931
HIGH FREQUENCY DRIVER:	LE20-1
Diaphragm Kit:	D8RLE20
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	6
Sweep Frequency Hz:	1000-6000
D.C. Resistance Ohms:	3.7 min/4.2 max
Gap Gauge:	.029"
Notes:	Test With Network
If Not Serviceable, Replace With:	035TiA
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Use as last resort. Replace both units in a stereo pair.
Additional Parts Currently Available*:	
Trim Ring:	21600

SYSTEM SPECIFICATIONS:

Nom. Impedance:	
Rec. Amp Power:	
Crossover Frequencies:	
Sensitivity:	Not Available
Enclosure Dim:	
Shipping Weight:	

*Other parts may also be available. Check with JBL for details.