


## CARD OUTLINE DESCRIPTION

CON1 — HARD DISK IN-USE LED CONNECTOR  
 CON2 — IDE HARD DISK DRIVER CONNECTOR  
 CON3 — FLOPPY DISK DRIVER CONNECTOR  
 CON4 — RS232 SERIAL PORT 1  
 CON5 — RS232 SERIAL PORT 2  
 CON6 — GAME PORT  
 CON7 — PRINTER PORT

## PORT ADDRESS and IRQ LEVEL

PORT	ADDRESS	IRQ LEVEL
FDD	PRIMARY 3F8H-3F7H	IRQ6
	SECONDARY 378H-377H	
IDE HD	PRIMARY IDE1 1F8H-1F7H	IRQ14
	IDE1 9F6H, 9F7H	
	SECONDARY IDE1 178H-177H	
	IDE1 376H, 377H	
ASYN1	COM1 3F8H-3F7H	IRQ4
	COM3 3E8H-3E7H	
ASYN2	COM2 2F8H-2F7H	IRQ3
	COM4 2E8H-2E7H	
GAME	201H	

## CARD OUTLINE



## FUNCTION DESCRIPTION

- 1st SERIAL INTERFACE:  
RS232 SERIAL PORT ASYNCHRONOUS
- 2nd SERIAL INTERFACE:  
RS232 SERIAL PORT ASYNCHRONOUS
- FLOPPY DISK DRIVE CONTROL PORT:  
SUPPORT BOTH OF THE 5.25" AND 3.5" DISKETTES DRIVERS WHICH FROM 368K TO 1.44M BYTES
- PARALLEL PORT:  
STANDARD PARALLEL PRINTER PORT
- IDE HARD DISK DRIVER INTERFACE:  
SUPPORT UP TO TWO IDE HARD DISK DRIVERS
- GAME (JOY-STICK) INTERFACE:  
SUPPORT "TWO BOTTOM-ONE STICK" JOY-STICK

## JUMPER SETTING

JP1	JP2	JP3	JP4	JP5	JP6	JP7	JP8	REMARK
⌋								FDD PORT 3F8H-3F7H SELECTED
⌋								FDD PORT 378H-377H SELECTED
⌋	⌋							HDD IDE ENABLE
	⌋							HDD IDE DISABLE
		⌋						ASYN1 ENABLE
		⌋						ASYN1 DISABLE
			⌋					3F8H-3FFHCOM1] SELECTED
			⌋					3E8H-3EFHCOM3] SELECTED
				⌋				ASYN2 ENABLE
				⌋				ASYN2 DISABLE
					⌋			2F8H-2FFHCOM2] SELECTED
					⌋			2E8H-2EFHCOM4] SELECTED
						⌋		PRINTER PORT ENABLE
						⌋		PRINTER PORT DISABLE
							⌋	378H-37FH[LTP2]
							⌋	276H-276H[LTP3]