

D - 39 DISPLAY & CABLE ASSEMBLY INSTRUCTION

PRESETTING OF NORMAL & TURBO FREQUENCY

TURBO LOW

(TENS PLACE)

| | | | | | | | | | | | | | | |
|---|---------------------------|---|---|---|---|---|---|---|---|---|---|---|---|---|
| 1 | A | 2 | 3 | 1 | C | 2 | 3 | 1 | E | 2 | 3 | 1 | G | 2 |
| + | 3 | 2 | B | 1 | 3 | 2 | D | 1 | 3 | 2 | F | 1 | 3 | |
| - | | | | | | | | | | | | | | |
| S | +&- TO POWER SUPPLY 5v. | | | | | | | | | | | | | |
| | S TO MAINBOARD TURBO LED- | | | | | | | | | | | | | |
| L | L TO TURBO LED- | | | | | | | | | | | | | |
| P | P TO TURBO LED+ | | | | | | | | | | | | | |
| H | 3 | 2 | B | 1 | 3 | 2 | D | 1 | 3 | 2 | F | 1 | 3 | |
| 1 | A | 2 | 3 | 1 | C | 2 | 3 | 1 | E | 2 | 3 | 1 | G | 2 |

TURBO HIGH

(TENS PLACE)

| | | | | | | | | | | | | | | |
|---|---------------------------|---|---|---|---|---|---|---|---|---|---|---|---|---|
| 2 | A | 1 | 3 | 2 | C | 1 | 3 | 2 | E | 1 | 3 | 2 | G | 1 |
| + | 3 | 1 | B | 2 | 3 | 1 | D | 2 | 3 | 1 | F | 2 | 3 | |
| - | | | | | | | | | | | | | | |
| S | +&- TO POWER SUPPLY 5v. | | | | | | | | | | | | | |
| | S TO MAINBOARD TURBO LED- | | | | | | | | | | | | | |
| L | P TO TURBO LED+ | | | | | | | | | | | | | |
| P | H TO TURBO LED- | | | | | | | | | | | | | |
| H | 3 | 1 | B | 2 | 3 | 1 | D | 2 | 3 | 1 | F | 2 | 3 | |
| 2 | A | 1 | 3 | 2 | C | 1 | 3 | 2 | E | 1 | 3 | 2 | G | 1 |

NORMAL.....

TURBO.....

| | X | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 0 |
|---|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|
| X | I | 10 1C | 1A 1B 1D 1E 1G | 1A 1B 1C 1D 1G | 1B 1C 1F 1G | 1A 1C 1D 1F 1G | 1A 1C 1D 1E 1F 1G | 1A 1B 1C | 1A 1B 1C 1D 1E 1F | 1A 1B 1C 1D 1F 1G | 1A 1B 1C 1D 1E 1F |
| 1 | 2B 2C | 3B 3C | 1A 3B 2C 1D 1E 1G | 1A 3B 3C 1D 1G | 3B 3C 1F 1G | 1A 2B 3C 1D 1F 1G | 1A 2B 3C 1D 1E 1F 1G | 1A 3B 3C 1D 1E 1F 1G | 1A 3B 3C 1D 1E 1F 1G | 1A 3B 3C 1D 1F 1G | 1A 3B 3C 1D 1E 1F 1G |
| 2 | 2A 2B 2D 2E 2G | 2A 3B 1C 2D 2E 2G | 3A 3B 3D 3E 3G | 3A 3B 1C 3D 2E 3G | 2A 3B 1C 2D 2E 1F 3G | 3A 2B 1C 3D 2E 1F 3G | 3A 2B 1C 3D 3E 1F 3G | 3A 3B 1C 3D 3E 1F 3G | 3A 3B 1C 3D 3E 1F 3G | 3A 3B 1C 3D 2E 1F 3G | 3A 3B 1C 3D 3E 1F 3G |
| 3 | 2A 2B 2C 2D 2G | 2A 3B 3C 2D 2G | 3A 3B 2C 3D 1E 3G | 3A 3B 3C 3D 3G | 2A 3B 3C 2D 1F 3G | 3A 2B 3C 3D 1F 3G | 3A 2B 3C 3D 1E 1F 3G | 3A 3B 3C 3D 2E 3G | 3A 3B 3C 3D 1E 1F 3G | 3A 3B 3C 3D 1F 3G | 3A 3B 3C 3D 1E 1F 3G |
| 4 | 2B 2C 2F 2G | 3B 3C 2F 2G | 1A 3B 2C 1D 1E 2F 3G | 1A 3B 3C 1D 2F 3G | 3B 3C 3F 3G | 1A 2B 3C 1D 3F 3G | 1A 2B 3C 1D 1E 3F 3G | 1A 3B 3C 1D 2F 2G 3G | 1A 3B 3C 1D 1E 3F 3G | 1A 3B 3C 1D 3F 3G | 1A 3B 3C 1D 1E 3F 3G |
| 5 | 2A 2C 2D 2E 2G | 2A 1B 3C 2D 2F 2G | 3A 1B 2C 3D 1E 2F 3G | 3A 1B 3C 3D 2F 3G | 2A 1B 3C 2D 3F 3G | 3A 3C 3D 3F 3G | 3A 3C 3D 1E 3F 3G | 3A 1B 3C 3D 2F 2G | 3A 1B 3C 3D 1E 3F 3G | 3A 1B 3C 3D 3F 3G | 3A 1B 3C 3D 1E 3F 3G |
| 6 | 2A 2C 2D 2E 2F 2G | 2A 1B 3C 2D 2E 2F 2G | 3A 1B 2C 3D 3E 2F 3G | 3A 1B 3C 3D 2E 2F 3G | 2A 1B 3C 2D 2E 3F 3G | 3A 3C 3D 2E 3F 3G | 3A 3C 3D 3E 3F 3G | 3A 1B 3C 3D 2E 2F 3G | 3A 1B 3C 3D 3E 3F 3G | 3A 1B 3C 3D 2E 3F 3G | 3A 1B 3C 3D 3E 3F 3G |
| 7 | 2A 2B 3C | 2A 3B 3C | 3A 3B 2C 1D 1E 1G | 3A 3B 3C 1D 1G | 2A 3B 3C 1F 1G | 3A 2B 3C 1D 1F 1G | 3A 2B 3C 1D 1E 1F 1G | 3A 3B 3C 1D 1E 1F 1G | 3A 3B 3C 1D 1E 1F 1G | 3A 3B 3C 1D 1F 1G | 3A 3B 3C 1D 1E 1F 1G |
| 8 | 2A 2B 2C 2D 2E 2F 2G | 2A 3B 3C 2D 2E 2F 2G | 3A 3B 2C 3D 3E 2F 3G | 3A 3B 3C 3D 2E 2F 3G | 2A 3B 3C 2D 2E 3F 3G | 3A 2B 3C 3D 2E 3F 3G | 3A 2B 3C 3D 3E 3F 3G | 3A 3B 3C 2D 2E 2F 2G | 3A 3B 3C 3D 3E 3F 3G | 3A 3B 3C 3D 2E 3F 3G | 3A 3B 3C 3D 3E 3F 3G |
| 9 | 2A 2B 2C 2D 2F 2G | 2A 3B 3C 2D 2F 2G | 3A 3B 2C 3D 1E 2F 3G | 3A 3B 3C 3D 2F 3G | 2A 3B 3C 2D 3F 3G | 3A 2B 3C 3D 3F 3G | 3A 2B 3C 3D 1E 3F 3G | 3A 3B 3C 2D 2F 2G | 3A 3B 3C 3D 1E 3F 3G | 3A 3B 3C 3D 3F 3G | 3A 3B 3C 3D 1E 3F 3G |
| 0 | 2A 2B 2C 2D 2E 2F | 2A 3B 3C 2D 2E 2F | 3A 3B 2C 3D 3E 2F 1G | 3A 3B 3C 3D 2E 2F 1G | 2A 3B 3C 2D 2E 3F 1G | 3A 2B 3C 3D 2E 3F 1G | 3A 2B 3C 3D 3E 3F 1G | 3A 3B 3C 2D 2E 2F 1G | 3A 3B 3C 3D 3E 3F 1G | 3A 3B 3C 3D 2E 3F 1G | 3A 3B 3C 3D 3E 3F 1G |