

SONY

Video Products Service Bulletin

Sony Service Company - Technical Services
A Division of Sony Corporation of America
Sony Drive, Park Ridge, New Jersey 07656

Model: SLV-353UC/555UC/757UC

No.118

Subject: Units Do Not Accept User Commands

Date: July 13, 1990

Symptom:
(12)

The unit will not accept any user commands until it is unplugged and plugged in again.

Solution: Add the following components to the circuits shown on the "MA" Boards of each model:

Description	Part Number	Quantity	
		SLV-353UC/757UC	SLV-555UC
Zener Diode RD6.2ES-BB2	8-719-109-93	1	2
Ceramic Capacitor 1000pF	1-102-074-00	2	2

FIG.1




Fig. 1 shows where the components should be installed on the "MA" Boards of the SLV-353UC and SLV-757UC.

FIG.2




Fig. 2 shows where the components should be installed on the "MA-34" Board of the SLV-555UC.