



PC 3000

16 ZONES

TO PROGRAM PC 3000

SEC.16 ZONE DEFINITION ZONES

TO ENTER ZONE DEFINITIONS FROM 1 TO 8
PRESS * 8 3000 16 (NOW ENTER EACH ZONE DEFINITION)

ZONE 1	---	---	ZONE DEFINITIONS
ZONE 2	---	---	DELAY = 00
ZONE 3	---	---	INSTANT = 01
ZONE 4	---	---	INSTANT/DLY = 02
ZONE 5	---	---	HOME/AWAY = 03
ZONE 6	---	---	
ZONE 7	---	---	
ZONE 8	---	---	

PRESS # # TO COMPLETE ENTRY

SEC.17 TO ENTER ZONE DEFINITIONS FROM ZONE 9 TO 16

PRESS * 8 3000 17 (NOW ENTER EACH ZONE DEFINITION)

ZONE 9	---	---
ZONE 10	---	---
ZONE 11	---	---
ZONE 12	---	---
ZONE 13	---	---
ZONE 14	---	---
ZONE 15	---	---
ZONE 16	---	---

PRESS # # TO COMPLETE ENTRY

SEC.18 1ST SYSTEM OPTION CODES FROM 1 TO 8

PRESS * 8 3000 18
THE FOLLOWING LIGHTS MUST BE ON (PRESS APPROPRIATE KEYS
TO SWITCH LIGHTS ON OR OFF)

ZONE 1	DISABLE COMMUNICATION
ZONE 5	NORMALLY CLOSED SWITCHES NO RESISTORS
ZONE 6	MAKES KEYPAD PANIC AUDIBLE

PRESS # # TO COMPLETE ENTRY

